
B.E.G. LUXOMAT®

PD4-M-TRIO-DALI/DSI-SM/-FC





(i) PRODUCT INFORMATION

- Occupancy detector for two lighting groups, for daylight-dependent lighting control, with additional output
- DALI/DSI interface for control of digital dimmable electronic ballasts as a group
- One common detection area
- Can be switched between DALI and DSI modes with remote control and Dip switches.
- Control of up to 25 digital dimming electronic ballasts and control modules as a group per DALI output 1 and 2, and up to 10 for DALI output 3
- Installation as Master
- Detection area can be extended with Slave units
- Push button manual switching and dimming available
- Additional functions can be set via optional remote control

■ TECHNICAL DATA

(~) 110-240 V AC , 50 / 60 Hz

 \Box

ca. 2W

.

360°

Ø 24 m across

Ø 8 m towards

Ø 6 4 m soutos

Ø 6,4 m seated

IP □ S

SM= IP20 FC= IP20 / Class II



-25 °C to +50 °C

Housing UV- and shock resistant polycarbonate



IR-PD4-TRIO-DALI

Cannel 1 to Cannel 2 (control the lighting)



max. 25 DALI/DSI-EVG each channel

1 - 60 min





10 - 2000 Lux

Channel 3 (control the lighting)

1/

max. 10 DALI/DSI EB





Description	Colour	Part number
PD4-M-TRIO-DALI/DSI-FC	white	92755
PD4-M-TRIO-DALI/DSI-SM	white	92750
Accessory (optional)		
IR-PD4-TRIO-DALI	grey	92104
Wire basket BSK (Ø 200 x 100)	white	92199
Wire basket BSK (Ø 164 x 143)	white	92467
Socket IP54 for PD4-TRIO-SM	white	92386