
B.E.G. LUXOMAT®

PD2-M-2C-11-48V-SM/-FC



FC RC



PRODUCT INFORMATION

- Occupancy detector with operating voltage of 11-48 V
- Two potential-free channels
- For channel 1, output of brightness-dependent resistance value also available, for additional analogue connection
- Can be used as either Master or Slave
- Push button manual switching available
- Additional functions can be set via optional remote control

■ TECHNICAL DATA

~ 11 -

11 - 48 V AC, DC

 \odot

< 1W

360°

Ø 10 m across

Ø 6 m towards Ø 4 m seated

Ø 4 III S

IP 🗆

SM= IP20 FC= IP20 / Class II

IR-PD-2C, IR-PD-Mini

Channel 1 to Channel 2 (control the lighting potential free)

Channel 1: 15 s - 30 min or pulse


3A-Version: $3 \text{ A cos } \phi = 1$


RR-Version: with Reed-Relais, 100 mA, $\cos \varphi = 1$

Housing UV- and shock resistant polycarbonate

Channel 2: Alarm pulse, pulse or 5 - 120 min

10 - 2000 Lux





Description	Colour	Part number
PD2-M-2C-11-48V-3A-FC	white	92164
PD2-M-2C-11-48V-RR-FC	white	92306
PD2-M-2C-11-48V-3A-SM	white	92154
PD2-M-2C-11-48V-RR-SM	white	92305
Accessory (optional)		
IR-PD-2C	grey	92475
IR-PD-Mini	grey	92159
Wire basket BSK (Ø 200 x 100)	white	92199
Socket IP54 for PD2- and PD4-SM	white	92161