
## B.E.G. LUXOMAT®


## PD4-M-DUO-DIM-SM/-FC/-FM











## *i* PRODUCT INFORMATION

- Occupancy detector for two separate lighting groups, for daylight-dependent lighting control
- Two 1-10 V interfaces for control of dimmable electronic ballasts
- One common detection area
- Two independent, movable light sensors
- Push button manual switching and dimming available
- Installation as Master
- Detection area can be extended with Slave units
- Additional functions can be set via optional remote control

## **■ TECHNICAL DATA**

110-240 V AC , 50 / 60 Hz

**(¹)** ca. 0.5W

360°

Ø 24 m across

Ø 8 m towards

Ø 6,4 m small movements

IP SM= IP44 FC= IP20 FM= IP20 / Class II

\_\_\_\_\_\_--25 °C to +50 °C

Housing UV- and shock resistant polycarbonate

IR-PDim, IR-PD-DIM-Mini


Channel 1 and Cannel 2 (control the lighting)


2300 W,  $\cos \varphi = 1$ 1150 VA,  $\cos \varphi = 0.5$ 

1 - 30 min

( 10 - 2000 Lux

2 dim outputs 1-10 V DC, max. 50 EB's





Description	Colour	Part number
PD4-M-DUO-DIM-FC	white	92272
PD4-M-DUO-DIM-SM	white	92271
PD4-M-DUO-DIM-FM	white	92273
Accessory (optional)		
IR-PDim	grey	92200
IR-PD-DIM-Mini	grey	92098
Wire basket BSK (Ø 200 x 100)	white	92199